


NOTES:

1. DISPLAY TYPE:
2. LCD OPERATING VOLTAGE:
3. OPERATING TEMPERATURE:
4. STORAGE TEMPERATURE:
5. DRIVE MODE:
6. VIEWING DIRECTION:
7. POLARIZER TYPE:
8. CONNECTOR:
9. CUSTOMER NO.:

  
**FUTURE S&T(SHEN ZHEN)CO.,LCD**  
 TEL: +86-755-29675886, FAX: +86-755-29675495

DESIGNED BY: <b>QWQWQ</b>	VERSION: 1.0
Y00007T-11	NO. 1 OF 2
CHECKED BY:	UNIT: MM
	DATE: 2005-07-06

STN(Y/G)

- 4.4V
- 20°C~70°C
- 30°C~80°C
- 1/16D,1/4B
- 6:00

SCALE: 3:1

TRANSPARENT, POSITIVE  
 ZEBRA  
 HS6636

1	2	3	4	5	6	7	8	9	10	88	89	90	91	92	93	94	95	96
-	-	-	-	-	-	-	CDM1	1-1	1-2	1-80	-	-	-	-	-	-	-	-
-	-	-	-	-	-	CDM2	-	2-1	2-2	2-80	-	-	-	-	-	-	-	-
-	-	-	-	-	CDM3	-	-	3-1	3-2	3-80	-	-	-	-	-	-	-	-
-	-	-	-	CDM4	-	-	-	4-1	4-2	4-80	-	-	-	-	-	-	-	-
-	-	-	CDM5	-	-	-	-	5-1	5-2	5-80	-	-	-	-	-	-	-	-
-	-	CDM6	-	-	-	-	-	6-1	6-2	6-80	-	-	-	-	-	-	-	-
-	CDM7	-	-	-	-	-	-	7-1	7-2	7-80	-	-	-	-	-	-	-	-
CDM8	-	-	-	-	-	-	-	8-1	8-2	8-80	-	-	-	-	-	-	-	-
-	-	-	-	-	-	-	-	9-1	9-2	9-80	CDM9	-	-	-	-	-	-	-
-	-	-	-	-	-	-	-	10-1	10-2	10-80	-	CDM10	-	-	-	-	-	-
-	-	-	-	-	-	-	-	11-1	11-2	11-80	-	-	CDM11	-	-	-	-	-
-	-	-	-	-	-	-	-	12-1	12-2	12-80	-	-	-	CDM12	-	-	-	-
-	-	-	-	-	-	-	-	13-1	13-2	13-80	-	-	-	-	CDM13	-	-	-
-	-	-	-	-	-	-	-	14-1	14-2	14-80	-	-	-	-	-	CDM14	-	-
-	-	-	-	-	-	-	-	15-1	15-2	15-80	-	-	-	-	-	-	CDM15	-
-	-	-	-	-	-	-	-	16-1	16-2	16-80	-	-	-	-	-	-	-	CDM16

97	98	99	100	101	102	103	104	105	106	184	185	186	187	188	189	190	191	192
-	-	-	-	-	-	-	-	17-80	17-79	17-1	-	-	-	-	-	-	-	CDM1-1
-	-	-	-	-	-	-	-	18-80	18-79	18-1	-	-	-	-	-	-	-	CDM2-1
-	-	-	-	-	-	-	-	19-80	19-79	19-1	-	-	-	-	-	-	-	-
-	-	-	-	-	-	-	-	20-80	20-79	20-1	-	-	-	-	CDM4-1	-	-	-
-	-	-	-	-	-	-	-	21-80	21-79	21-1	-	-	-	CDM5-1	-	-	-	-
-	-	-	-	-	-	-	-	22-80	22-79	22-1	-	CDM6-1	-	-	-	-	-	-
-	-	-	-	-	-	-	-	23-80	23-79	23-1	-	CDM7-1	-	-	-	-	-	-
-	-	-	-	-	-	-	-	24-80	24-79	24-1	CDM8-1	-	-	-	-	-	-	-
CDM9-1	-	-	-	-	-	-	-	25-80	25-79	25-1	-	-	-	-	-	-	-	-
-	CDM10-1	-	-	-	-	-	-	26-80	26-79	26-1	-	-	-	-	-	-	-	-
-	-	CDM11-1	-	-	-	-	-	27-80	27-79	27-1	-	-	-	-	-	-	-	-
-	-	-	CDM12-1	-	-	-	-	28-80	28-79	28-1	-	-	-	-	-	-	-	-
-	-	-	-	CDM13-1	-	-	-	29-80	29-79	29-1	-	-	-	-	-	-	-	-
-	-	-	-	-	CDM14-1	-	-	30-80	30-79	30-1	-	-	-	-	-	-	-	-
-	-	-	-	-	-	CDM15-1	-	31-80	31-79	31-1	-	-	-	-	-	-	-	-
-	-	-	-	-	-	-	CDM16-1	32-80	32-79	32-1	-	-	-	-	-	-	-	-



FUTURE S&T(SHEN ZHEN)CO.,LCD  
 TEL: +86-755-29675886, FAX: +86-755-29675495

DESIGNED BY:


QWQWQ

Y00007T-11

VERSION: 1.0

NO. 2 OF 2

CHECKED BY:



UNIT: MM

DATE: 2005-07-06